

LINDRIVE 12V & 24V DIMMER COMPATIBILITY

About Dimmer Compatibility

The dimmers listed below were tested with the specified Magnitude LED drivers. We are constantly adding to our list of compatible dimmers.

This chart describes the lowest measured electrical output when using the dimmer/driver combination. Some dimmers have wider dimming range. Zero (0%) means dim to off. One percent (1%) and five percent (5%) provide good dimming range. However, these percentages do not accurately describe the perception of the lamp, which is subjective to the individual viewer.

This compatibility list also takes into account other quality considerations such as flicker or pulsation. We do not recommend dimmers with these issues. In those cases where a dimmer is not compatible, we have suggested an alternate Magnitude product.

Minimum Dimming Percentage				
DIMMER TYPE	LinDrive 12V Models		LinDrive 24V Models	
	SLT20L12DC	SLT40L12DC	SLT20L24DC	SLT40L24DC
Lutron Caseta, Wireless PD-6WCL (MLV)	15%	20%	20%	25%
Lutron Maestro, Wireless MRF2-6CL (MLV)	20%	20%	25%	25%
Legrand Adorne ADWR700MMTU (MLV)	0%	0%	0%	0%
Lutron Radio RA2 RRD-6ND (MLV Result)	0%	5%	0%	10%
Lutron Maestro MA-600 (MLV)	Recommend E-Series	Recommend E-Series	Recommend E-Series	Recommend E-Series
Legrand Adorne ADTP703TUW4 (MLV)	25%	25%	25%	25%
Leviton Decore Smart DW6HD (MLV)	0%	0%	0%	0%
Lutron Nova T NTLV-600 (MLV)	20%	20%	20%	20%

Note: LinDrive supports MLV (Forward-Phase) dimming only.

LINDRIVE 12V & 24V DIMMER COMPATIBILITY

Minimum Dimming Percentage				
DIMMER TYPE	LinDrive 12V Models		LinDrive 24V Models	
	SLT20L12DC	SLT40L12DC	SLT20L24DC	SLT40L24DC
Leviton illumatech IPMO6 (MLV)	25%	25%	25%	25%
Lutron Ariadni AYLV-600P (MLV)	15%	25%	20%	22%
Lutron Diva DVLV-600P (MLV)	10%	15%	15%	20%
Lutron Caseta, Wireless PD-10NXD (MLV)	20%	25%	20%	25%
Lutron Maestro MA-PRO (MLV / ELV) MLV Mode	20%	25%	20%	25%
Lutron Radio RA2 RRD-PRO (MLV / ELV) MLV Mode	15%	20%	20%	20%
Lutron Caseta, Wireless PD-5NE (MLV / ELV) MLV Mode	20%	20%	20%	20%
Legrand Adorne ADTP700RMTUM1 (MLV)	0%	15%	5%	10%

Note: LinDrive supports MLV (Forward-Phase) dimming only.