

# E-SERIES 24V DC Installation Guide

## 20W - 96W Class 2 Voltage LED Drivers (UL Recognized)

### BEFORE YOU BEGIN



#### General

This driver is to be installed in accordance with Article 450 of the National Electric Code (NEC). The driver must be installed in a well-ventilated area free from explosive gases and vapors. Proper operation requires for free flow of air. Since this driver is hardwired, it should only be installed by a qualified electrician.

#### Precautions Before Installing

Check the label and ensure the driver has the proper input voltage and wattage for the job. Check the wire markings to ensure they match the wiring diagram (below).

#### Input Connections / Grounding

With power turned off, connect one wire to black (line) and one wire to white (neutral). Use only UL listed wire nuts and connectors. Connect the ground wire to the driver's green wire.

#### Output Connections

Connect the LED wires to the driver wires; positive (+) to the red wire and negative (-) to purple wire.

#### Quick Specs

Input Voltage	120V AC
Output Voltage	24V DC
Operating Temperature	-30°C - +40°C (-22°F - 104°F)
Enclosure	IP67 - Wet Location
Dimensions (Inches)	4.92" x 2.2" x 0.77"
Weight	9 oz.

#### Dimming

Dimmable with any standard MLV / Incandescent TRIAC (Leading Edge) dimmer switch. Dimmer switch is to be installed on the Input (120VAC side) of the driver.

**NOTE:** Measuring the output voltage without a load will result in readings greater than the nominal voltage. **8W minimum load required.**

**Do not install PWM low voltage controllers on the output without consulting with Magnitude.**

